

TRMS DIGITAL MULTIMETER 1000Vac/dc

DMM3000



- True RMS
- LCD Display (6000 counts)
- AC/DC Voltage up to 1000 V
- AC/DC current up to 10A
- Capacitance, resistance, frequency measurements
- LoZ mode
- High Frequency Rejection
- Non contact voltage detection (Adjustable sensitivity)
- Built-in magnet sticker
- CATIV600V/CATIII1000V



DMM3000

TRMS DIGITAL MULTIMETER 1000Vac/dc

General	
Display	6000 counts
Auto power off	✓
Backlight	✓
Bargraph	✓
REL	✓
HOLD	✓
Diode and continuity test	✓
Auto-ranging	✓
Non Contact Voltage Detection	✓
LoZ mode	✓
Dimensions	74x156x44mm
Weight	250g
Batteries	9V battery (NEDA 1604A or IEC 6LF22)
Standards	EC 61010-1, IEC/EN61010-2-033
Desing	Holster with probe holder, tilt stand and magnetic sticker
Safety rating	CAT IV 600V, CAT III 1000V
Accesories included	Standard test leads, user manual, batteries

DMM3000

TRMS DIGITAL MULTIMETER 1000Vac/dc

Specs	
TRMS	✓
DC Voltage (mV)	600mV
DC Voltage (V)	1000V
AC Voltage (V)	1000V
DC Current	10A
AC Current	10A
Frequency	100kHz
Resistance	40MΩ
Diode	1,5V
Continuity	✓
Capacitance	10mF

Product Code Information	
SKU	KPSDMM3000CBINT
EAN code	8435394786421
UPC code	810053676936
Pcs/export carton	20